



ENERGY 650 START 230-400V 12-24V



Overview

ENERGY 650 START 230-400V 12-24V

cod. 829385

Battery charger and starter for charging free electrolyte batteries (WET) with 12/24V voltage and starting all kinds of cars, vans, light trucks, earth moving equipment, tractors and trucks.

Features:

- choice of normal charge, quick charge (BOOST), quick start
- timer for quick charge
- remote control
- display of charging and starting current
- protection against overloads and polarity reversal.



3 PH 230V-400V



CE MARKING



EAC CERTIFICATION



REMOTE CONTROLS

Technical data

CODE	CODE 829385	A_{EFF}	EFFECTIVE CHARGING CURRENT 100 A	ADJUSTMENT POSITIONS 5
V_{3PH}	THREE PHASE MAINS VOLTAGE 230 / 400 V	A_{EN}	RATED CHARGE CURR. EN60335-2-29 80 A	DIMENSIONS 36,5 x 46 x 75,5 cm
F	MAINS FREQUENCY 50 / 60 Hz	A_{1V/C}	START CURRENT 1V/C EN60335-2-29 640 A	WEIGHT 38 kg
P_{CHARGE}	CHARGE POWER 2,5 KW	A_{START MAX}	MAX STARTING CURRENT 1000 A	EAN CODE 800489774452 0



ENERGY 650 START 230-400V 12-24V



START POWER 20 KW



MIN. RATED REFERENCE CAPACITY 20 A



PIECES/PALLET 9 pz/pallet



CHARGING VOLTAGE 12 / 24 V



MAX RATED REFERENCE CAPACITY 1200 / 800 A



PIECES/PALLET - B 6 pz/pallet-B

Included Accessories

REMOTE CONTROL 6 M - 123993